

ANSI_ANSLG C82.11-2011

American National Standard for Lamp Ballasts - High Frequency Fluorescent Lamp Ballasts





ANSI_ANSLG C82.11-2011

Revision of ANSI C82.11 Consolidated-2002

American National Standard

for lamp ballasts—

High Frequency Fluorescent
Lamp Ballasts

American National Standard

Approval of an American National Standard requires verification by ANSI that the requirements for due process, consensus, and other criteria for approval have been met by the standards developer. An American National Standard implies a consensus of those substantially concerned with its scope and provisions. Consensus is established when, in the judgment of the ANSI Board of Standards Review, substantial agreement has been reached by directly and materially affected interests. Substantial agreement means much more than a simple majority, but not necessarily unanimity. Consensus requires that all views and objections be considered, and that a concerted effort be made toward their resolution. The existence of an American National Standard does not in any respect preclude anyone, whether s/he has approved the standard or not, from manufacturing, marketing, purchasing, or using products, processes, or procedures not conforming to the standards. It is intended as a guide to aid the manufacturer, the consumer, and the general public.

The American National Standards Institute does not develop standards and will in no circumstances give an interpretation of any American National Standard. Moreover, no person shall have the right or authority to issue an interpretation of an American National Standard in the name of the American National Standards Institute. Requests for interpretations should be addressed to the Committee Secretariat referred to on the title page.

CAUTION NOTICE: This American National Standard may be revised or withdrawn at any time. The procedures of the American National Standards Institute require that action be taken periodically to reaffirm, revise, or withdraw this standard. Purchasers of American National Standards may receive current information on all standards by calling or writing the American National Standards Institute.

Copyright ©2011 by American National Standard Lighting Group
All rights reserved.

No part of this publication may be reproduced in any form,
in an electronic retrieval system or otherwise, without
prior written permission of the publisher.
Printed in the United States of America

Foreword (This foreword is not part of American National Standard C82.11-2011)

Suggestions for improvement of this standard should be submitted to the Secretariat C78, American National Standard Lighting Group, 1300 North 17th Street, Suite 1752, Rosslyn, VA 22209.

This standard was processed and approved by the Accredited Standards Committee on lamp ballasts, C82, and its Working Group C82WG01. Working Group approval of the standard does not necessarily imply that all working group members voted for that approval.

This 2011 edition is the revision of its predecessor, the ANSI C82.11 Consolidated-2002. This is the third revision of the first edition of 1993. The 2011 edition includes changes to paragraph 1.2, Annex “A” and all Figures “C”. In the matter of the figure rework, most of that work was nothing more than an electronic redrawing of the 1993 drawings.

The reader will note that changes have been marked by redline.

Amendment / Change	CDV	RV
Revision/Consolidation	CDV 82_m742	RV 82_m743

Robert Erhardt, Chair, ASC82
Ernesto Mendoza, Technical Advisor and Draftsman
Randolph N. Roy, ANSLG Secretariat
Matt Clark, ANSLG Senior Editor

Table of Contents

Foreword.....	3
1.0 Scope.....	9
1.2 Important Patent Disclaimer.....	9
2.0 Normative references.....	9
3.0 Characteristics	10
3.1 Input power factor	10
3.1.1 High frequency current crest factor	10
4.0 Ballast Marking	10
4.1 Marking	10
4.1.1 Power factor	10
4.1.2 High-frequency	10
4.2 Color coding of ballast leads	11
4.2.1 Supply leads.....	11
4.2.2 Lamp lead wires – table 1.....	11
4.2.3 Other ballast types.....	12
Table 1 – Color coding for lamp leads	12
5.0 Ballast Performance.....	13
5.1 General	13
5.2 Starting conditions.....	13
5.2.1 Starting	13
5.2.2 Fixture and circuit grounding	13
5.2.3 Lamp starting time vs. starting current requirement	13
5.3 Ballast Output.....	14
5.3.1 Ballast Factor (Relative Lamp light output).....	15
5.3.2 Lamp light output.....	15
5.3.3 Lamp current	15
5.4 Cathode preheating current	15
5.5 Regulation	15
5.5.1 Rapid-start ballasts.....	15
5.5.2 Instant-start ballasts	16
5.6 Operating-current waveshape	16
5.6.1 Normal operating conditions.....	16
5.6.2 Special operating condition	16
5.7 Supplementary cathode heating.....	16
5.7.1 Switch-start ballasts.....	16
5.7.2 Rapid-start ballasts.....	16
5.8 Electro-magnetic interference suppression	17

5.9 Ballast safety	17
5.10 Input current, harmonic distortion	17
5.11 Line transient requirements	17
5.12 Inrush currents	18
Table 2 – Bulk energy capacitances	18
Table 3 – Peak current requirements	18
5.13 Ballast efficiency	19
6.0 Design Center Voltages	19
7.0 Application Requirements	19
7.1 Wiring and contact resistance requirements	19
7.2 Operating temperature limits	20
7.3 Supply voltage limits	20
7.3.1 Average voltage for satisfactory ballast operation	20
7.3.2 Voltage excursions	20
7.4 Equipment grounding	20
7.5 Audible sound level	20
8.0 End of Life	21
8.1 Asymmetric pulse test	21
8.2 Asymmetric power test	21
8.3 Open filament test	21
Figure 1a Rapid Start Time (t) Definitions	22
Figure 1b Instant Start Time (t) Definitions	23
Annexes	24
Annex A (Normative) Specification for Low Voltage Control Interface for Controllable Ballasts	25
A1.0 Purpose	25
A2.0 Definitions	25
A2.1 Controllable ballasts	25
A2.2 Control terminals	25
A2.3 Control signal	25
A2.4 Maximum value of lamp power (of a controllable ballast)	25
A2.5 Minimum value of lamp power (of a controllable ballast)	25
A3.0 Control Methods	25
A3.1 Control by D.C. voltage (ANSI Type 1)	25
A3.2 Voltage specifications	25
A3.3 Control input current limits	26
A3.4 Switch-on	26
A3.5 Lead wire colors	26

A3.6 Control by future types of controls (ANSI Type xx).....	26
Figure A-1	27
Figure A-2	27
Figure A-3	28
Annex B (Informative) Specification for Marking Nomenclature for Controllable Ballasts	29
B1.0 Purpose	29
B2.0 Technical Parameters.....	29
B2.1 Power source.....	29
B2.2 Circuit type.....	29
B2.2.1 High voltage	29
B2.2.2 High voltage, carrier current	29
B2.2.3 Low voltage	29
B3.0 Current type.....	30
B4.0 Modulation type	30
B5.0 Range of varying voltage	30
B6.0 Nomenclature of designation	30
B6.1 Examples	30
B7.0 Administration of this document	30
B7.1 Revision	30
Figure B-1	31
Annex C (Normative) Method of Measurement.....	32
C1.0 Pertinent measurements	32
C2.0 Electrical supply characteristics.....	32
C2.1 Test voltage and rated frequency	32
C2.2 Line-voltage waveshape.....	33
C3.0 Ambient conditions for lamp measurements	33
C3.1 General.....	33
C3.2 Temperature	33
C3.3 Drafts	33
C3.4 Lamp position	34
C4.0 Reference lamps	34
C4.1 Choice of lamps	34
C4.2 Lamp connections	34
C4.2.1 Preheat-start lamps	34
C4.2.2 Instant-start and cold-cathode lamps.....	34
C5.0 Reference ballasts.....	35
C5.1 General characteristics, $f_o = 60\text{Hz}$	35

C5.2 General characteristics, $f_o = 25\text{KHz}$	35
C5.3 Rapid-start, preheat, and instant-start circuit	35
C5.4 Test-circuit 60 Hz reference ballast	36
C5.5 Test-circuit 25 KHz reference ballast	36
C5.6 Connection pins	37
C5.7 Instruments	37
C6.0 Test Measurements – High Frequency Commercial Electronic Ballast	38
C6.1 General	38
C6.2 Connection of test ballast to lamp pins	38
C6.3 Rapid-start ballast and program start ballast	38
C6.4 Instant-start ballast	38
C6.5 Preheat-start ballast	38
C7.0 Ballast output (ballast factor)	38
C7.1 Electronic ballast output	38
C7.2 High-current lamps	39
C7.3 Ballast regulation	40
C8.0 Lamp Current	40
C8.1 Rapid-start	41
C8.2 Instant-start	41
C8.3 Crest factor	41
C8.4 Waveshape determination	42
C9.0 Cathode heat	42
C9.1 Cathode heat – normal operation	43
C9.2 Cathode heat rapid-start ballast type – dummy load operation	43
C10.0 Lamp starting tests using electronic ballasts – lamp starting time vs. starting current	43
C10.1 Rapid-start lamps ballast, program-start ballast and programmed ballast	44
C10.2 Cathode heat – dummy load operation for programmed-start and modified rapid-start ballasts	44
C10.3 Starting Scenarios	44
C10.3.2 Rapid-start ballast	44
C10.3.2.1 Preheat time (T_1 - T_2)	44
C10.3.2.2 Glow current	45
C10.3.2.3 Glow to arc transition (T_2 - T_3)	46
C10.3.2.4 Instant-start	46
C10.3.2.5 Filament resistance cold to hold ratio	46
C11.0 Ballast Input	48
C11.1 Input current	48
C11.2 Input power	48
C11.3 Power factor	49
C11.4 Input current THD (Total Harmonic Distortion)	49
C11.5 Inrush current (NEMA 410 applies)	50
C11.6 Indirect verification	50
C11.7 Inrush current model basics	50
C11.8 Inrush current model calibration	51

C11.9 Direct testing measurement.....	52
C11.10 BEF (Ballast Efficacy Factor).....	53
C12.0 Line Transients.....	53
C13.0 Conducted emissions testing	54
C14.0 EOL (End of Life).....	54
C14.1 Asymmetric pulse test	54
C14.2 Asymmetric power test	55
C14.3 Open filament test	56
Figures.....	59
Figure C-1: Dummy Load Connection.....	60
Figure C-2: Single Lamp Connection	61
Figure C-3: Rapid Start and Program Start.....	62
Figure C-4: Reference Ballast	63
Figure C-5: H.F. Reference Ballast.....	64
Figure C-6: Crest Factor Measurement	65
Figure C-7: Preheat Time	66
Figure C-8: Instant Start.....	67
Figure C-9: Inrush Current One Ballast Model.....	68
Figure C-10: Inrush Current Multiple Ballast Model	69
Figure C-11: Asymmetric Pulse Test Circuit	70
Figure C-12: Asymmetric Power Test	71
Figure C-13: Open Filament Test (a)	72
Figure C-14: Open Filament Test (b)	73
Figure C-15: Open Filament Lamp Current Detection Test.....	74

1.0 Scope

1.1 This standard is intended to cover high frequency ballasts which have rated open-circuit voltages of 2000 volts or less, operate the lamp at frequencies between 10 kHz and 500 kHz., and are intended to operate at a supply frequency of 50 Hz or 60 Hz. This comprises ballasts for hot-cathode fluorescent lamps, either switch-start (preheat-start), rapid-start (continuously heated cathodes), modified rapid start, programmed start, or instant start used primarily for lighting purposes. The ballast and lamp combinations covered by this specification are normally intended for use in room ambient temperatures of 10°C to 40°C. At ambient temperatures outside this range, certain special operating characteristics may be required.

1.2 Important Patent Disclaimer

It is possible that some of the elements of this document may be the subject of patent rights. When this document was approved for publication, ANSLG did not know of any patent applications, patents pending, or existing patents. ANSLG shall not be held responsible for identifying any or all such patent rights.

2 Normative references

The following standards contain provisions, which through reference in this text constitute provisions of this American National Standard. At the time of publication, the editions indicated were valid. All standards are subject to revision, and parties to agreements based on this American National Standard are encouraged to investigate the possibility of applying the most recent edition of the standards indicated below.

ANSI/NFPA No. 70-2008, *National Electrical Code*

ANSI/IEEE C62.41-2002 (Parts 1 & 2), *Guide for Surge Voltages in Low-Voltage AC Power Circuits*

ANSI_IEC C78.81-2010, *Double-capped Fluorescent Lamps—Dimensional and Electrical Characteristics*

ANSI_IEC C78.901-2005, *Single Base Fluorescent Lamps—Dimensional and Electrical Characteristics*

ANSI C82.2-2002, *American National Standard Methods of Measurement of Fluorescent Lamp Ballasts*

ANSI C82.3-2002, *American National Standard Specification for Fluorescent Lamp Reference Ballasts*

ANSI C82.13-2002, *Definitions for fluorescent lamps and ballasts*

ANSI C82.77-2002, *Harmonic Emission Limits—Related Power Quality Requirements for Lighting Equipment*